

120W CLASS D MIXER AMPLIFIER WITH MUSIC SOURCE

A120MD

cod. 1300-112040



240W CLASS D MIXER AMPLIFIER WITH MUSIC SOURCE

A240MD

cod. 1300-124020



TECHNICAL SPECIFICATIONS

RMS power	120W(A120MD) - 240W(A240MD)
Frequency response	80Hz-16KHz (+1dB, -3dB)
THD	≤ 0.05% (at 1KHz, 1/3 rated power)
Constant imp. speakers outputs	4 Ω, 16 Ω
Constant volt. speakers outputs	100 V
Protections	overheating, overload, short circuit
Signal LED	signal, peak, protection, power
Disturb/signal	(MIC 1,2,3) ≥ 66dB - (AUX1,2) ≥ 85dB
AUX input sensitivity	350mV±20mV/10KΩ
MICRO input sensitivity	5mV±1mV/600Ω
Phantom power supply	24Vdc
Power supply from AC mains	230Vac - 50-60Hz
Consumption	160VA(A120MD) - 300VA(A240MD)
Dimensions (WxHxD)	484x300x44mm
Colour	black
Weight	4,7Kg(A120MD) - 5,2Kg(A240MD)

120W - 240W mixer-amplifier with 4 electronically balanced MIC inputs on screw clamps with micro-switch phantom voltage, 2 AUX inputs on RCA connections for medium and high stereo sources lines. There is a muting clamp and an EMC clamp for maximum priority on the other inputs. For the use of BM1 microphone unit, add the article CDINRJ45 (code 1800-303010). Electronic Ding-Dong incorporated. Unbalanced stereo output on RCA connectors. It is also provided with separated volume controls for each channel, general tone control, master volume and LED signal indicators for: active signal, peak, protection and power supply. It has got FM/AM radio, USB reader, SD card reader and Bluetooth receiver. Power outputs for constant impedance and constant voltage lines. Standard support for rack installation included. Size: 1 r.u.