

120W + 120W MIXER AMPLIFIER/MULTIMEDIA PLAYER

MP2120 BT

cod. 1300-212020



Desktop microphone unit product BM2

› p. 37



TECHNICAL SPECIFICATIONS

AUX input sensitivity	-34 + +14dBu; 15mV + 3,8V
MICRO input sensitivity	-50 + -2dBu; 2,5 + 500mV
Balanced input impedance	10KΩ
Phantom power supply	24Vdc
Bass control	±12dB a 60Hz
Treble control	±12dB a 10KHz
SEND and RETURN levels	+0dBu; 775mV
PRE OUT noise, channels 1-4	-60dBu
PRE OUT noise, AUX level	-73dBu
Response in frequency (-3 dB)	80 + 15KHz
Rating power distortion 1KHz	<1%
MICRO signal/noise ratio	>60dB
AUX signal/noise ratio	>80dB
Multimedia player	AM/FM digital tuner, auto tune, Bluetooth, MP3, USB, SD, MMC
Rating power RMS	2X120W
I.H.F. power	2X180W
Speaker outputs, constant imp.	4Ω
Speaker outputs, constant volt.	70V, 100V
Power supply from AC mains	230Vac - 50+60Hz
Power consumption	450VA
Dimensions (WxHxD)	443x88x380mm
Colour: black	black
Weight: 12,0Kg	12,00Kg

Music and announcements for bars, restaurants, gyms, beauty salons, shops, supermarkets, offices. Amplified 120W+120W dual channel receiver with two electronically balanced MIC inputs on 3-pin XLR connectors with sensitivity control and phantom power and micro-switch ON/OFF control, an AUX input on RCA connectors for medium and high-level stereo line sources, a TEL input with adjustable sensitivity control and vox control, an electronically balanced MC/LINE input on RJ45 jack connector for microphone base for selective priority calls and activation of integrated electronic ding-dong signal.

It features two PRE-OUTPUTS. And it also features separate volume controls for each input channel, general tone controls and master volume for each output. Digital FM/AM tuner, CD/MP3 player with USB, integrated SD/MMC card slots and Bluetooth receiver.

Supplied with IR remote control. Electronically-controlled forced ventilation cooling. Dual power output for constant impedance and constant voltage lines. It needs KMR2 for rack assembly and also KSA for proper support. Size: 2 r.u.